

Annex A - Migrations Matrix

MIGRATION SCENARIOS

Losing SP(s)		Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note		
FROM NB	SP	FROM BB	SP	TO NB	SP	TO BB	SP			Number Retention	Number Port (direct)	Number Return to Rangeholder	Number Subsequent Port	
Cable	SP1	Cable	SP1	MPF	SP2	MPF	SP2	None	MPF New Line / Stopped line provide.		X (if cable range)	X (if MPF CP owns range)	X (If a non cable range)	
Cable	SP1	Cable	SP1	WLR2	SP2			None	WLR New Line / Stopped line provide.		X (if cable range)	X (if BT owns range)	X (If a non cable range)	
Cable	SP1	Cable	SP1	WLR3	SP2			None	WLR New Line / Stopped line provide.		X (if cable range)	X (if BT owns range)	X (If a non cable range)	
Cable	SP1	Cable	SP1	WLR2	SP2	SMPF	SP2	None	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if BT owns range)	X (if BT owns range)	X (If a non cable range)	
Cable	SP1	Cable	SP1	WLR2	SP2	SMPF	SP3	None	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if cable range)	X (if BT owns range)	X (If a non cable range)	
Cable	SP1	Cable	SP1	WLR3	SP2	SMPF	SP2	None	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if cable range)	X (if BT owns range)	X (If a non cable range)	
Cable	SP1	Cable	SP1	WLR3	SP2	SMPF	SP3	None	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if cable range)	X (if BT owns range)	X (If a non cable range)	
MPF	SP1	MPF	SP1	Cable	SP2	Cable	SP2	None	Cable line install		X (if MPF CP's range)	X (if cable range)	x (if non MPF provider number)	
MPF	SP1	MPF	SP1	MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if MPF CP's range)	X (if MPF GCP owns range)	x (if non MPF provider number)	
MPF	SP1	MPF	SP1	WLR2	SP2			AOT	WLR New Line / Stopped line provide.		X (if MPF CP's range)	X (if BT owns range)	x (if non MPF provider number)	
MPF	SP1	MPF	SP1	WLR3	SP2			AOT	WLR New Line / Stopped line provide.		X (if MPF CP's range)	X (if BT owns range)	x (if non MPF provider number)	
MPF	SP1	MPF	SP1	WLR2	SP2	SMPF	SP2	AOT	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if MPF CP's range)	X (if BT owns range)	x (if non MPF provider number)	
MPF	SP1	MPF	SP1	WLR2	SP2	SMPF	SP3	AOT	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if MPF CP's range)	X (if BT owns range)	x (if non MPF provider number)	
MPF	SP1	MPF	SP1	WLR3	SP2	SMPF	SP2	AOT	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if MPF CP's range)	X (if BT owns range)	x (if non MPF provider number)	

Annex A - Migrations Matrix

Losing SP(s)				Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note
MPF	SP1	MPF	SP1	WLR3	SP2	SMPF	SP3	AOT	WLR New Line / Stopped line provide WITH SIM PROVIDE of SMPF		X (if MPF CP's range)	X (if BT owns range)	x (if non MPF provider number)	
PSTN	SP1			Cable	SP2	Cable	SP2	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
PSTN	SP1			MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if BT Number range)		X (if not BT number range)	
PSTN	SP1			WLR2	SP2			AOT	WLR Transfer	X				
PSTN	SP1			WLR3	SP2			AOT	WLR Transfer	X				
PSTN	SP1			WLR2	SP2	SMPF	SP2	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
PSTN	SP1			WLR2	SP2	SMPF	SP3	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
PSTN	SP1			WLR3	SP2	SMPF	SP2	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
PSTN	SP1			WLR3	SP2	SMPF	SP3	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR2	SP1			Cable	SP2	Cable	SP2	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
WLR2	SP1			MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if BT Number range)	X (if MPF GCP owns range)	X (if not BT number range)	
WLR2	SP1			WLR2	SP2			AOT	WLR Transfer	X				
WLR2	SP1			WLR3	SP2			AOT	WLR Transfer	X				
WLR2	SP1			WLR2	SP2	SMPF	SP2	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR2	SP1			WLR2	SP2	SMPF	SP3	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR2	SP1			WLR3	SP2	SMPF	SP2	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR2	SP1			WLR3	SP2	SMPF	SP3	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR3	SP1			Cable	SP2	Cable	SP2	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
WLR3	SP1			MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if BT Number range)	X (if MPF GCP owns range)	X (if not BT number range)	

Annex A - Migrations Matrix

Losing SP(s)				Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note
WLR3	SP1			WLR2	SP2			AOT	WLR Transfer	X				
WLR3	SP1			WLR3	SP2			AOT	WLR Transfer	X				
WLR3	SP1			WLR2	SP2	SMPF	SP2	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR3	SP1			WLR2	SP2	SMPF	SP3	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR3	SP1			WLR3	SP2	SMPF	SP2	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
WLR3	SP1			WLR3	SP2	SMPF	SP3	AOT	WLR Transfer WITH SIM PROVIDE of SMPF	X				
PSTN	SP1	SMPF	SP1	Cable	SP2	Cable	SP2	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
PSTN	SP1	SMPF	SP1	MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if BT Number range)		X (if not BT number range)	
PSTN	SP1	SMPF	SP1	WLR2	SP2			AOT	WLR Transfer with SMPF cease	X				
PSTN	SP1	SMPF	SP1	WLR3	SP2			AOT	WLR Transfer with SMPF cease	X				
PSTN	SP1	SMPF	SP1	PSTN	SP1	SMPF	SP2	MAC	SMPF Migrate order	X				
PSTN	SP1	SMPF	SP1	WLR2	SP2	SMPF	SP2	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
PSTN	SP1	SMPF	SP1	WLR2	SP2	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
PSTN	SP1	SMPF	SP1	WLR3	SP2	SMPF	SP2	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
PSTN	SP1	SMPF	SP1	WLR3	SP2	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
PSTN	SP1	SMPF	SP2	Cable	SP3	Cable	SP3	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
PSTN	SP1	SMPF	SP2	MPF	SP3	MPF	SP3	AOT	MPF Migrate order		X (if BT Number range)	X (if MPF GCP owns range)	X (if not BT number range)	

Annex A - Migrations Matrix

Losing SP(s)				Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note
PSTN	SP1	SMPF	SP2	WLR2	SP3			AOT	WLR Transfer with SMPF cease	X				
PSTN	SP1	SMPF	SP2	WLR3	SP3			AOT	WLR Transfer with SMPF cease	X				
PSTN	SP1	SMPF	SP2	PSTN	SP1	SMPF	SP3	MAC	SMPF Migrate order	X				
PSTN	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP2	AOT	WLR Transfer	X				
PSTN	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
PSTN	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP4	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
PSTN	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP2	AOT	WLR Transfer	X				
PSTN	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
PSTN	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP4	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR2	SP1	SMPF	SP1	Cable	SP2	Cable	SP2	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
WLR2	SP1	SMPF	SP1	MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if BT Number range)	X (if MPF GCP owns range)	X (if not BT number range)	
WLR2	SP1	SMPF	SP1	WLR2	SP2			AOT	WLR Transfer with SMPF cease	X				
WLR2	SP1	SMPF	SP1	WLR3	SP2			AOT	WLR Transfer with SMPF cease	X				
WLR2	SP1	SMPF	SP1	WLR2	SP1	SMPF	SP2	MAC	SMPF Migrate order	X				
WLR2	SP1	SMPF	SP1	WLR2	SP2	SMPF	SP2	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR2	SP1	SMPF	SP1	WLR2	SP2	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				

Annex A - Migrations Matrix

Losing SP(s)				Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note
WLR2	SP1	SMPF	SP1	WLR3	SP2	SMPF	SP2	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR2	SP1	SMPF	SP1	WLR3	SP2	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR2	SP1	SMPF	SP2	Cable	SP3	Cable	SP3	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
WLR2	SP1	SMPF	SP2	MPF	SP3	MPF	SP3	AOT	MPF Migrate order		X (if BT Number range)		X (if not BT number range)	
WLR2	SP1	SMPF	SP2	WLR2	SP3			AOT	WLR Transfer with SMPF cease	X				
WLR2	SP1	SMPF	SP2	WLR3	SP3			AOT	WLR Transfer with SMPF cease	X				
WLR2	SP1	SMPF	SP2	WLR2	SP1	SMPF	SP3	MAC	SMPF Migrate order	X				
WLR2	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP2	AOT	WLR Transfer	X				
WLR2	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR2	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP4	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR2	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR2	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP4	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR3	SP1	SMPF	SP1	Cable	SP2	Cable	SP2	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
WLR3	SP1	SMPF	SP1	MPF	SP2	MPF	SP2	AOT	MPF Migrate order		X (if BT Number range)	X (if MPF CP owns range)	X (if not BT number range)	
WLR3	SP1	SMPF	SP1	WLR2	SP2			AOT	WLR Transfer with SMPF cease	X				

Annex A - Migrations Matrix

Losing SP(s)				Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note
WLR3	SP1	SMPF	SP1	WLR3	SP2			AOT	WLR Transfer with SMPF cease	X				
WLR3	SP1	SMPF	SP1	WLR2	SP2	SMPF	SP2	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR3	SP1	SMPF	SP1	WLR2	SP2	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR3	SP1	SMPF	SP1	WLR3	SP1	SMPF	SP2	MAC	SMPF Migrate order	X				
WLR3	SP1	SMPF	SP1	WLR3	SP2	SMPF	SP2	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR3	SP1	SMPF	SP1	WLR3	SP2	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR3	SP1	SMPF	SP2	Cable	SP3	Cable	SP3	None	Cable line install		X (if BT Number range)	X (if previous cable number)	X (if not BT number range)	
WLR3	SP1	SMPF	SP2	MPF	SP3	MPF	SP3	AOT	MPF Migrate order		X (if BT Number range)	X (if MPF CP owns range)	X (if not BT number range)	
WLR3	SP1	SMPF	SP2	WLR2	SP3			AOT	WLR Transfer with SMPF cease	X				
WLR3	SP1	SMPF	SP2	WLR3	SP3			AOT	WLR Transfer with SMPF cease	X				
WLR3	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP2	AOT	WLR Transfer	X				
WLR3	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				
WLR3	SP1	SMPF	SP2	WLR2	SP3	SMPF	SP4	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				
WLR3	SP1	SMPF	SP2	WLR3	SP1	SMPF	SP3	MAC	SMPF Migrate order	X				
WLR3	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP2	AOT	WLR Transfer	X				
WLR3	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP3	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by GCP	X				

Annex A - Migrations Matrix

Losing SP(s)				Gaining SP(s)				Consumer Protection	SP Guidance	Number Port Process Order Type(s)				Note
WLR3	SP1	SMPF	SP2	WLR3	SP3	SMPF	SP4	AOT for Voice MAC for SMPF	Sequential WLR transfer and SMPF. Either can be ordered first but it must close before the second is submitted. Controlled by EU	X				